

High Power Stationary 16Bands Jammer



130-2700 MHz

JTD-JM100-16

JIETONG DIGITAL

GET CONNECTED

16 Bands Jammer

This is a multi-Use, powerful Jammer. This jammer provides 16 bands of coverage (see below) with a total power output of 100 Watts.

This model is specialized to coverage mobile phone frequencies used in most parts of the world countries Europe, Asia, Australia, Middle East and Africa.

This unit will jam standard GSM ,3G, 4G and 4G LTE, 4G WiMAX all types of Android phones, Tablets, Smart Phones, iPhones, GPS, Tracking devices · remote control signals from various devices such as RC cars, RC boats, alarms, wireless sensors, amateur or professional remotely controlled toys, etc .

Creating a range of up to 70 meters in "forbidden" zone for all I mobiles, Wi-Fi, and tracking devices to provide you with complete coverage which giving you the privacy, security.

It Included vehicle power supply allows flexibility for you to take the unit with you and use it while mobile. Prevent "leakage" of important information along the way saving you from intrusive phone calls.

Key features

- Adjustable working range you can avoid blocking adjacent areas
- Multi-Use ,powerful Jammer
- Each of 18 frequency is separately and Adjustable
- Friendly use and maintenance
- 24/7 hours working, Could continue to work
- Good cooling system with unique case as big heat sink and 5 fans inside, low noise
- Portability: Vehicular power cable also included Could be used in Vehicle directly jamming car bomb



Specifications

Technical characteristics

- ✧ **Total Output Power:** 100W
- ✧ **Cover Radius:** 10-70m(under Signal level \leq -85dBm)@according to the signal density mobile network
- ✧ **Jamming type:** Sweep Jamming
- ✧ **Antenna Type:** 3dBi external omni-directional
- ✧ **Power Supply:** AC adapter (50 to 60Hz/100 to 240V AC-DC24V) with car charger
- ✧ **Electric Filed (SAR):** Compatible with ICNIRP Standards (Human safe)
- ✧ **Operating Temp:**-20 to +50℃
- ✧ **Storage Temp:**-40 to +60℃
- ✧ **Humidity:** 5%-80%
- ✧ **Dimension(LXWXH):** 445 x 272x 70mm not include antennas
- ✧ **Inner box dimension:**445x4280x80mm
- ✧ **Weight:**10kg
- ✧ **List of Frequency and RF Output Power**

| | | | |
|---------------|---------------|---------------|---------------|
| 130-190 MHz | 190-290 MHz | 290-400 MHz | 400-500 MHz |
| 5W | 5W | 5W | 5W |
| 820-880 MHz | 925-960 MHz | 1805-1880 MHz | 2100-2200 MHz |
| 8 W | 8 W | 8w | 8w |
| 2300-2500 MHz | 2500-2700 MHz | 3700-3800 MHz | 5100-5500 MHz |
| 8 W | 8 W | 4 W | 4 W |
| 5500-5900 MHz | 1805-1880 MHz | 2100-2200 MHz | 2500-2700 MHz |
| 4 W | 8 W | 8 W | 8 W |

- ✧ **Package contents:**
 - ✓ Signal Jammer x1pcs
 - ✓ AC Charger x1pcs
 - ✓ Car Charger cable x1pcs
 - ✓ Red infrared remote control x1pcs
 - ✓ Antennas x16pcs

Notices:

1. Before linking all the antennas, power supply shall not be switched on at first. Non taking off antenna when the mainframe is in the working condition.
2. The jammer shall be installed in the position with good ventilation. And large-scale things shall be avoided to ensure to the shielding effect.
3. When use the jammer outdoors, preventing water shall be taken into consideration.

Applications

It can be applied in a meeting room, conference room, museum, gallery, theater, concert hall, church, temple, restaurant, classroom, training center, factory, bank, train, car, bus, etc.

